


BR-6428nS V2 BR-6428nC

Guide d'installation rapide

08-2013 / v1.0


Contenu de l'emballage

Avant d'utiliser ce produit, veuillez vérifier que rien ne manque dans l'emballage et contacter votre revendeur pour lui réclamer les éléments manquants le cas échéant :




BR-6428nS V2
(2 antennes 5 dBi)


ou



BR-6428nC
(2 antennes 9 dBi)



Adaptateur



Câble Ethernet




Guide d'installation




CD-ROM

Installation

1. Branchez l'adaptateur secteur fourni dans la prise d'alimentation 5 Vcc de l'appareil et branchez l'autre extrémité dans une prise de courant.



2. Assurez-vous que le voyant est allumé. Si ce n'est pas le cas, l'appareil n'est pas branché correctement.




3. Utilisez un périphérique Wi-Fi (par ex. ordinateur, tablette, smartphone) pour rechercher le réseau Wi-Fi ayant le SSID « edimax.setup » puis connectez-vous à celui-ci.


 ***iOS 4 ou Android 4 et plus sont nécessaires pour la configuration sur un smartphone ou une tablette.***

4. Ouvrez un navigateur Internet et saisissez l'adresse ***http://edimax.setup*** si vous n'arrivez pas directement à l'écran « Pour commencer » indiqué ci-dessous, puis cliquez sur « **Pour commencer** » pour commencer l'opération de configuration.



 ***Si vous ne pouvez pas accéder à <http://edimax.setup>, veuillez vous assurer que votre ordinateur est configuré pour utiliser une adresse IP dynamique. Il s'agit d'une procédure simple et les instructions pas à pas se trouvent dans le manuel de l'utilisateur.***

5. Sélectionnez un mode pour votre BR-6428nS V2/nC et cliquez sur « **Suivant** » pour continuer.




Routeur Wi-Fi	<i>L'appareil se connecte à votre modem et active l'accès à Internet (sans fil et Ethernet) pour les périphériques de votre réseau.</i>
Point d'accès	<i>L'appareil se connecte à un routeur existant par câble Ethernet et fournit l'accès à Internet (sans fil et Ethernet) pour les périphériques de votre réseau.</i>
Répéteur	<i>L'appareil se connecte sans fil à votre réseau existant et répète le signal sans fil.</i>

6. Suivez les instructions sur l'écran pour terminer la configuration. Pour plus d'informations, veuillez consulter le manuel de l'utilisateur.


Interface de configuration basée sur navigateur

Après la configuration, vous pouvez accéder à l'interface de configuration basée sur navigateur pour configurer ou modifier les paramètres du BR-6428nS V2/nC. Pour accéder à l'interface de configuration basée sur navigateur, saisissez ***http://edimax.setup*** dans la barre d'adresse d'un navigateur Internet sur un périphérique réseau connecté au BR-6428nS V2/nC.



 ***Si vous ne pouvez pas accéder à edimax.setup, connectez le BR-6428nS V2/nC à un ordinateur à l'aide d'un câble Ethernet et réessayez.***

Il vous est demandé de saisir un nom d'utilisateur et un mot de passe. Le nom d'utilisateur par défaut est **admin** et le mot de passe par défaut est **1234**.



Vous accéderez à l'écran « État » indiqué ci-dessous. Utilisez le menu en bas à gauche pour naviguer. Pour plus d'informations, consulter le manuel utilisateur.

Status [Help](#)

- ▶ Setup Wizard
- ▶ Internet
- ▶ LAN
- ▶ 2.4GHz Wireless
- ▶ Firewall
- ▶ QoS
- ▶ Advance
- ▶ Administration

System Status


System		LAN	
Model	BR-6428nS V2	IP Address	192.168.2.1
Current Time	2013/7/10 10:25:46	Subnet Mask	255.255.255.0
Hardware Version	Rev. A	DHCP Server	Enable
Firmware Version	1.01	MAC Address	80:1F:02:00:00:0B

Internet		2.4GHz Wireless	
IP Address Mode	Dynamic IP Connect	ESSID	edimax setup
IP Address	192.168.4.128	Channel Number	2
Subnet Mask	255.255.255.0	Security	WPA Pre-shared Key
Default Gateway Address	192.168.4.254	MAC Address	801f0200000b
MAC Address	80:1F:02:00:00:0C		
Primary DNS	192.168.1.12		
Secondary DNS	192.168.1.2		
Third DNS			

Dépannage

1. En mode répéteur, comment puis-je me connecter à un réseau dont le SSID est masqué ?

- Durant la configuration iQ sélectionnez « Configurer le répéteur manuellement » comme indiqué ci-dessous. Saisissez manuellement le SSID du réseau masqué, un SSID pour votre appareil et les informations de cryptage pour le réseau masqué.



SSID	Saisissez le SSID (nom du réseau) du réseau existant masqué.
SSID de l'appareil	Saisissez un SSID pour le BR-6428Ns V2/nC ou laissez-le vide pour utiliser un SSID par défaut composé du SSID de votre routeur existant (ci-dessus) suivi de « _2EX ».
Encodage	Saisissez les informations de cryptage de votre réseau existant masqué.

2. Je ne parviens pas à accéder à Internet.

- Assurez-vous que tous les câbles sont correctement branchés. Essayez un câble Ethernet différent.
- Vérifier que vous pouvez accéder à l'interface web de configuration. Si ce n'est pas le cas, veuillez vous assurer que votre ordinateur est configuré pour utiliser une adresse IP dynamique. Consultez le manuel de l'utilisateur pour plus de conseils si vous n'êtes pas sûr de la marche à suivre.

- c. Connectez-vous à l'interface web de configuration et allez dans **Internet > Configuration WAN** puis vérifiez que le type de connexion est correct. Si vous n'êtes pas sûr de votre type de connexion, veuillez contacter votre fournisseur d'accès à Internet (FAI).
- d. Connectez votre ordinateur directement à votre modem et vérifiez si vous avez accès à Internet. Dans le cas contraire, veuillez contacter votre fournisseur d'accès à Internet pour obtenir de l'aide.

3. Je ne parviens pas à ouvrir l'interface web e configuration.

- a. Veuillez vous assurer que votre ordinateur est configuré pour utiliser une adresse IP dynamique. Consultez le manuel de l'utilisateur pour plus de conseils si vous n'êtes pas sûr de la marche à suivre.

4. Comment puis-je rétablir les paramètres par défaut de mon appareil ?

- a. Pour réinitialiser les paramètres d'usine de l'appareil, maintenez enfoncé la touche WPS/Reset pendant 10 secondes jusqu'à ce que le voyant d'alimentation commence à clignoter. Veuillez patienter quelques minutes pendant que l'appareil redémarre. Lorsque l'appareil redémarre, tous les paramètres sont réinitialisés. Les paramètres par défaut sont affichés sur l'étiquette à l'arrière du produit, comme indiqué ci-dessous :



Connexion au routeur	Saisissez cette URL dans un navigateur pour exécuter la configuration iQ ou configurer les paramètres avancés. Vous devez être connecté à l'appareil par Wi-Fi ou câble Ethernet.
Nom d'utilisateur/mot de passe	Il s'agit du nom d'utilisateur et du mot de passe par défaut pour accéder à l'interface de configuration à base de navigateur lorsque vous accédez à l'URL « Connexion au routeur » (ci-dessus).
Nom du réseau Wi-Fi	Il s'agit du nom de réseau Wi-Fi par défaut pour l'appareil. Recherchez ce nom (SSID) et connectez-vous afin d'accéder à l'URL « Connexion au routeur » (ci-dessus).
MAC	L'adresse MAC est unique pour chaque appareil et elle est utilisée pour l'identification au sein d'un réseau. L'adresse MAC unique de votre appareil est affichée ici.
CODE PIN	Il s'agit du code PIN de votre appareil pour la configuration Wi-Fi protégée (WPS).

5. J'ai oublié mon mot de passe.

- a. Rétablissez les paramètres par défaut du routeur. Le nom d'utilisateur par défaut est **admin** et le mot de passe par défaut est **1234**. Les paramètres par défaut sont affichés sur l'étiquette à l'arrière du produit, comme indiqué ci-dessus.

6. Mon BR-6428nS V2/nC possède un signal sans fil faible en mode répéteur.

- a. Les signaux faibles sont généralement causés par des interférences provenant d'autres appareils ou par les obstacles qui obstruent le signal sans fil du BR-6428nS V2/nC :
- b. Tenez l'appareil éloigné de tout autre appareil radio, comme les fours microondes ou les téléphones sans fil.
- c. Ne placez pas l'appareil dans le coin d'une pièce ni au-dessous ou à proximité de métal.
- d. Assurez-vous qu'il ait le moins d'obstacles possible entre le BR-6428nS V2/nC et votre appareil réseau sans fil.

En mode répéteur, le faible signal du BR-6428nS V2/nC peut être à son tour causé par un faible signal provenant de votre routeur existant. Il est important de choisir

un bon emplacement pour le BR-6428nS V2/nC *en fonction de votre routeur sans fil existant*. Le meilleur emplacement est environ à mi-chemin entre votre routeur sans fil existant et la zone que vous voulez couvrir avec le BR-6428nS V2/nC. S'il est trop éloigné du routeur existant, le BR-6428nS V2/nC aura des difficultés à recevoir le signal sans fil.

7. Les ports WAN et LAN fonctionnent-ils de la même manière selon les différents modes de l'appareil ?

Non, les ports WAN et LAN possèdent des fonctions légèrement différentes selon le mode de fonctionnement de l'appareil.

- a. En mode **routeur Wi-Fi**, le **port WAN** sert à la connexion directe avec votre modem xDSL. Les **ports LAN** servent pour les clients réseau filaires.
- b. En mode **point d'accès**, le **port WAN** n'est pas utilisé. Connectez votre routeur existant sur un **port LAN** de l'appareil et connectez les autres clients réseau filaires aux autres **ports LAN**.
- c. En mode **répéteur**, le **port WAN** n'est pas utilisé et les **ports LAN** servent pour les clients réseau filaires. Ne connectez pas votre routeur existant aux **ports WAN** ou **LAN**, car cela pourrait causer un dysfonctionnement de l'appareil.

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Reorient or relocate the receiving antenna.
2. Increase the separation between the equipment and receiver.
3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
4. Consult the dealer or an experienced radio technician for help.

FCC Caution

This device and its antenna must not be co-located or operating in conjunction with any other antenna or transmitter. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Any changes or modifications not expressly approved by the party responsible for compliance could void the authority to operate equipment.

Federal Communications Commission (FCC) Radiation Exposure Statement

This equipment complies with FCC radiation exposure set forth for an uncontrolled environment. In order to avoid the possibility of exceeding the FCC radio frequency exposure limits, human proximity to the antenna shall not be less than 2.5cm (1 inch) during normal operation.

Federal Communications Commission (FCC) RF Exposure Requirements

This EUT is compliance with SAR for general population/uncontrolled exposure limits in ANSI/IEEE C95.1-1999 and had been tested in accordance with the measurement methods and procedures specified in OET Bulletin 65 Supplement C. The equipment version marketed in US is restricted to usage of the channels 1-11 only. This equipment is restricted to *indoor* use when operated in the 5.15 to 5.25 GHz frequency range.

R&TTE Compliance Statement

This equipment complies with all the requirements of DIRECTIVE 1999/5/EC OF THE EUROPEAN PARLIAMENT AND THE COUNCIL of March 9, 1999 on radio equipment and telecommunication terminal equipment and the mutual recognition of their conformity (R&TTE). The R&TTE Directive repeals and replaces in the directive 98/13/EEC (Telecommunications Terminal Equipment and Satellite Earth Station Equipment) As of April 8, 2000.

Safety

This equipment is designed with the utmost care for the safety of those who install and use it. However, special attention must be paid to the dangers of electric shock and static electricity when working with electrical equipment. All guidelines of this and of the computer manufacture must therefore be allowed at all times to ensure the safe use of the equipment.

EU Countries Intended for Use

The ETSI version of this device is intended for home and office use in Austria, Belgium, Bulgaria, Cyprus, Czech, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Turkey, and United Kingdom. The ETSI version of this device is also authorized for use in EFTA member states: Iceland, Liechtenstein, Norway, and Switzerland.

EU Countries Not Intended for Use

None

EU Declaration of Conformity

- English:** This equipment is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC, 2009/125/EC.
- Français:** Cet équipement est conforme aux exigences essentielles et autres dispositions de la directive 1999/5/CE, 2009/125/CE
- Čeština:** Toto zařízení je v souladu se základními požadavky a ostatními příslušnými ustanoveními směrnic 1999/5/ES, 2009/125/ES.
- Polski:** Urządzenie jest zgodne z ogólnymi wymaganiami oraz szczególnymi warunkami określonymi Dyrektywą UE 1999/5/EC, 2009/125/EC
- Română:** Acest echipament este în conformitate cu cerințele esențiale și alte prevederi relevante ale Directivei 1999/5/CE, 2009/125/CE.
- Русский:** Это оборудование соответствует основным требованиям и положениям Директивы 1999/5/EC, 2009/125/EC.
- Magyar:** Ez a berendezés megfelel az alapvető követelményeknek és más vonatkozó irányelveknek (1999/5/EK, 2009/125/EC)
- Türkçe:** Bu cihaz 1999/5/EC, 2009/125/EC direktifleri zorunlu istekler ve diğer hükümlerle ile uyumludur.
- Українська:** Обладнання відповідає вимогам і умовам директиви 1999/5/EC, 2009/125/EC.
- Slovenčina:** Toto zariadenie spĺňa základné požiadavky a ďalšie príslušné ustanovenia smerníc 1999/5/ES, 2009/125/ES.
- Deutsch:** Dieses Gerät erfüllt die Voraussetzungen gemäß den Richtlinien 1999/5/EC, 2009/125/EC.
- Español:** El presente equipo cumple los requisitos esenciales de la Directiva 1999/5/EC, 2009/125/EC.
- Italiano:** Questo apparecchio è conforme ai requisiti essenziali e alle altre disposizioni applicabili della Direttiva 1999/5/CE, 2009/125/CE.
- Nederlands:** Dit apparaat voldoet aan de essentiële eisen en andere van toepassing zijnde bepalingen van richtlijn 1999/5/EC, 2009/125/EC.
- Português:** Este equipamento cumpre os requisitos essenciais da Directiva 1999/5/EC, 2009/125/EC
- Norsk:** Dette utstyret er i samsvar med de viktigste kravene og andre relevante regler i Direktiv 1999/5/EC, 2009/125/EC.
- Svenska:** Denna utrustning är i överensstämmelse med de väsentliga kraven och övriga relevanta bestämmelser i direktiv 1999/5/EG, 2009/125/EG.
- Dansk:** Dette udstyr er i overensstemmelse med de væsentligste krav og andre relevante forordninger i direktiv 1999/5/EC, 2009/125/EC.
- Suomi:** Tämä laite täyttää direktiivien 1999/5/EY, 2009/125/EY oleelliset vaatimukset ja muut asiaankuuluvat määräykset.

FOR USE IN 



WEEE Directive & Product Disposal



At the end of its serviceable life, this product should not be treated as household or general waste. It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for disposal.

Declaration of Conformity

We, Edimax Technology Co., Ltd., declare under our sole responsibility, that the equipment described below complies with the requirements of the European R&TTE directives.

Equipment: N300 Multi-Function Wi-Fi Router

Model No.: BR-6428nS V2 / BR-6428nC

The following European standards for essential requirements have been followed:

Directives 1999/5/EC

Spectrum : ETSI EN 300 328 V1.8.1 (2012-04);
EMC : EN 301 489-1 V1.9.2 (2011-09);
EN 301 489-17 V2.2.1 (2012-09);
Safety (LVD) : IEC 60950-1:2005 (2nd Edition);
EN 60950-1:2006+A11:2009+A1:2010+A12:2011

Recommendation 99/519/EC

EMF : EN 50385: 2002

Directives 2006/95/EC

Safety (LVD) : IEC 60950-1:2005 (2nd Edition);
EN 60950-1:2006+A11:2009+A1:2010+A12:2011

Edimax Technology Co., Ltd.
No. 3, Wu Chuan 3rd Road,
Wu-Ku Industrial Park,
New Taipei City, Taiwan



Date of Signature: September 6th, 2013

Signature: _____

A handwritten signature in black ink, appearing to read 'Albert Chang', written over a horizontal line.

Printed Name: Albert Chang

Title: Director

Edimax Technology Co., Ltd.

Notice According to GNU General Public License Version 2

This product includes software that is subject to the GNU General Public License version 2. The program is free software and distributed without any warranty of the author. We offer, valid for at least three years, to give you, for a charge no more than the costs of physically performing source distribution, a complete machine-readable copy of the corresponding source code.

Das Produkt beinhaltet Software, die den Bedingungen der GNU/GPL-Version 2 unterliegt. Das Programm ist eine sog. „Free Software“, der Autor stellt das Programm ohne irgendeine Gewährleistungen zur Verfügung. Wir bieten Ihnen für einen Zeitraum von drei Jahren an, eine vollständige maschinenlesbare Kopie des Quelltextes der Programme zur Verfügung zu stellen – zu nicht höheren Kosten als denen, die durch den physikalischen Kopiervorgang anfallen.

GNU GENERAL PUBLIC LICENSE

Version 2, June 1991

Copyright (C) 1989, 1991 Free Software Foundation, Inc. 51 Franklin Street, Fifth Floor, Boston, MA 02110-1301, USA
Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed.

Preamble

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public License is intended to guarantee your freedom to share and change free software--to make sure the software is free for all its users. This General Public License applies to most of the Free Software Foundation's software and to any other program whose authors commit to using it. (Some other Free Software Foundation software is covered by the GNU Lesser General Public License instead.) You can apply it to your programs, too.

When we speak of free software, we are referring to freedom, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs; and that you know you can do these things.

To protect your rights, we need to make restrictions that forbid anyone to deny you these rights or to ask you to surrender the rights. These restrictions translate to certain responsibilities for you if you distribute copies of the software, or if you modify it.

For example, if you distribute copies of such a program, whether gratis or for a fee, you must give the recipients all the rights that you have. You must make sure that they, too, receive or can get the source code. And you must show them these terms so they know their rights.

We protect your rights with two steps: (1) copyright the software, and (2) offer you this license which gives you legal permission to copy, distribute and/or modify the software.

Also, for each author's protection and ours, we want to make certain that everyone understands that there is no warranty for this free software. If the software is modified by someone else and passed on, we want its recipients to know that what they have is not the original, so that any problems introduced by others will not reflect on the original authors' reputations.

Finally, any free program is threatened constantly by software patents. We wish to avoid the danger that redistributors of a free program will individually obtain patent licenses, in effect making the program proprietary. To prevent this, we have made it clear that any patent must be licensed for everyone's free use or not licensed at all.

The precise terms and conditions for copying, distribution and modification follow.

TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION

0. This License applies to any program or other work which contains a notice placed by the copyright holder saying it may be distributed under the terms of this General Public License. The "Program", below, refers to any such program or work, and a "work based on the Program" means either the Program or any derivative work under copyright law: that is to say, a work containing the Program or a portion of it, either verbatim or with modifications and/or translated into another language. (Hereinafter, translation is included without limitation in the term "modification".) Each licensee is addressed as "you".

Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The act of running the Program is not restricted, and the output from the Program is covered only if its contents constitute a work based on the Program (independent of having been made by running the Program). Whether that is true depends on what the Program does.

1. You may copy and distribute verbatim copies of the Program's source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep

intact all the notices that refer to this License and to the absence of any warranty; and give any other recipients of the Program a copy of this License along with the Program.

You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

2. You may modify your copy or copies of the Program or any portion of it, thus forming a work based on the Program, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions:

- a) You must cause the modified files to carry prominent notices stating that you changed the files and the date of any change.
- b) You must cause any work that you distribute or publish, that in whole or in part contains or is derived from the Program or any part thereof, to be licensed as a whole at no charge to all third parties under the terms of this License.
- c) If the modified program normally reads commands interactively when run, you must cause it, when started running for such interactive use in the most ordinary way, to print or display an announcement including an appropriate copyright notice and a notice that there is no warranty (or else, saying that you provide a warranty) and that users may redistribute the program under these conditions, and telling the user how to view a copy of this License. (Exception: if the Program itself is interactive but does not normally print such an announcement, your work based on the Program is not required to print an announcement.)

These requirements apply to the modified work as a whole. If identifiable sections of that work are not derived from the Program, and can be reasonably considered independent and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Program, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it.

Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Program.

In addition, mere aggregation of another work not based on the Program with the Program (or with a work based on the Program) on a volume of a storage or distribution medium does not bring the other work under the scope of this License.

3. You may copy and distribute the Program (or a work based on it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you also do one of the following:

- a) Accompany it with the complete corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- b) Accompany it with a written offer, valid for at least three years, to give any third party, for a charge no more than your cost of physically performing source distribution, a complete machine-readable copy of the corresponding source code, to be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- c) Accompany it with the information you received as to the offer to distribute corresponding source code. (This alternative is allowed only for noncommercial distribution and only if you received the program in object code or executable form with such an offer, in accord with Subsection b above.)

The source code for a work means the preferred form of the work for making modifications to it. For an executable work, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the executable. However, as a special exception, the source code distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable.

If distribution of executable or object code is made by offering access to copy from a designated place, then offering equivalent access to copy the source code from the same place counts as distribution of the source code, even though third parties are not compelled to copy the source along with the object code.

4. You may not copy, modify, sublicense, or distribute the Program except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense or distribute the Program is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.

5. You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Program or its derivative works. These actions are prohibited by law if you do not accept this License. Therefore, by modifying or distributing the Program (or any work based on the Program), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Program or works based on it.

6. Each time you redistribute the Program (or any work based on the Program), the recipient automatically receives a license from the original licensor to copy, distribute or modify the Program subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties to this License.

7. If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Program at all. For example, if a patent license would not permit royalty-free redistribution of the Program by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Program.

If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply and the section as a whole is intended to apply in other circumstances.

It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of protecting the integrity of the free software distribution system, which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice.

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

8. If the distribution and/or use of the Program is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Program under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this License incorporates the limitation as if written in the body of this License.

9. The Free Software Foundation may publish revised and/or new versions of the General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Program specifies a version number of this License which applies to it and "any later version", you have the option of following the terms and conditions either of that version or of any later version published by the Free Software Foundation. If the Program does not specify a version number of this License, you may choose any version ever published by the Free Software Foundation.

10. If you wish to incorporate parts of the Program into other free programs whose distribution conditions are different, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

NO WARRANTY

11. BECAUSE THE PROGRAM IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE PROGRAM "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU. SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

12. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE PROGRAM AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PROGRAM (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE PROGRAM TO OPERATE WITH ANY OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.